



# Technical Service Bulletin

Date: 9/27/95

merit industries, inc.

- Problem:** Monitor is inoperative after power-up.
- Games affected:** All Megatouch games using Type 19 Ducksan monitors.
- Symptoms:** After power-up, you can hear the fan running and see the power supply light, but there is no picture.
- Cause:** Fuse on monitor chassis has blown.
- Solution:** Replace existing fast-blow 3 amp 250V fuse with a slow-blow 3 amp (or 3.15 amp) 250V fuse (5 x 20mm). If you do not have the proper fuse, call Merit Customer Service for assistance: 1-800-445-9353 (Merit part # EC3004).